

**List of Compatible Inverters  
with LG Chem Home Battery**

**RESU**

RESU3.3

RESU6.5

RESU10

RESU13

# Compatible storage Inverters with RESU LV

All RESU installations require a compatible inverter. Using a non-approved inverter will void the warranty provided by LG Chem. See below important instructions when installing and using RESU LV.

- 1) Battery inverters should operate in **On-Grid only. (Not in Off-Grid)**
- 2) For On-Grid applications where Back-up mode may be sometimes utilized the backed up circuits and inverters AC draw must not exceed the battery current limit specifications.

Following list of Inverters are currently compatible with LG Chem home battery, RESU LV Series.

※ More compatible inverters will be added.

INVERTER			BATTERY				REMARK
Brand	Model	Software Version*	RESU3.3 (3kW)	RESU6.5 (4.2kW)	RESU10 (5kW)	RESU13 (5kW)	
	Sunny Island 3.0M(EU)	3.110	○	○	○		*Cannot use in Back-up Mode
	Sunny Island 4.4M(EU)	3.00.03.R	○	○	○	○	*Cannot use in Back-up Mode
	Sunny Island 6.0H(EU)		○	○	○	○	*Exclusively, RESU13 can be used in Back-up Mode
	SH5K SH5K+	SH5K_V11_V1_A SH5K-V13_FW_V13	○	○	○		*Can use in Back-up Mode under the condition 2) above
	SH3K6 SH4K6 SH5K-20	SH3K6-V11_FW_V28 SH4K6-V11_FW_V28 SH5K-20_FW_V57	○	○	○	○	
	SK-SU5000E SK-SU3700E SK-SU3000E SK-TL5000E SK-TL3700E SK-TL3000E	Inverter_M V2.15 Charger_28035_M_2.23	○	○	○	○	*Can use in Back-up Mode under the condition 2) above
	ISS1Play 3TL ISS1Play 3 with Transformer ISS 1Play 6TL	FW : ABH1002_Z DFW : ABH1003_P D.BOOT : ABH100	○	○	○		*Can use in Back-up Mode under the condition 2) above
	MultiPlus 48/3000/35	CCGX v2.31	○	○	○		*Can use in Back-up Mode under the condition 2) above
	GW3048D-ES GW3648D-ES GW5048D-ES	FW : 15158 App : V3.6.3	○	○	○	○	*Can use in Back-up Mode under the condition 2) above
	GW3048-EM GW3648-EM GW5048-EM	FW : 06068 App : V3.6.3	○	○	○	○	
	GW3600S-BP GW5000S-BP	FW : 05058 App : V3.6.3		○	○	○	

\* Only compatible with the software versions which are mentioned above.







# Compatible storage Inverters with RESU LV

All RESU installations require a compatible inverter. Using a non-approved inverter will void the warranty provided by LG Chem. See below important instructions when installing and using RESU LV.

- 1) Battery inverters should operate in **On-Grid only. (Not in Off-Grid)**
- 2) For On-Grid applications where Back-up mode may be sometimes utilized the backed up circuits and inverters AC draw must not exceed the battery current limit specifications.

Following list of Inverters are currently compatible with LG Chem home battery, RESU LV Series.

※ More compatible inverters will be added.

INVERTER			BATTERY				REMARK
Brand	Model	Software Version*	RESU3.3 (3kW)	RESU6.5 (4.2kW)	RESU10 (5kW)	RESU13 (5kW)	
	SPMC481 SPMC482	SP Link : 11.15.7006	○	○	○	○	*Exclusively, can use in Off-Grid
	Leonardo Pro II 3000/48 Li	FW: 2648433 WRD: 2.1, WBM: 1A	○	○	○	○	*Cannot use in Back-up Mode *Exclusively, RESU13 can be used in Back-up Mode
	SE 5K-RWS SE 7K-RWS SE 8K-RWS SE 10K-RWS	4.7.28	○	○	○		*Cannot use in Back-up Mode
 	RHI-3K-48ES RHI-3.6K-48ES RHI-4.6K-48ES RHI-5K-48ES RHI-6K-48ES	270015	○	○	○	○	*Can use in Back-up Mode under the condition 2) above
	Hybrid Inverter 3.0-1 Hybrid Inverter 3.6-1 Hybrid Inverter 5.0-1	0909A	○	○	○	○	*Can use in Back-up Mode under the condition 2) above

\* Only compatible with the software versions which are mentioned above.

